

### SoftRock v5.0 Band Specific Component Values

#####

Band (MHz)	C22 (pF)	C23 (pF)	C24 (pF)	C25 (pF)	C27 (pF)	C28 (pF)	C29 (pF)	L21 (uH)	L21 wind/core	L22 (uH)	L22 wind/core	T21 core	T21 primary	T21 secondaries
1.800	470	470	220	620	6800	470	6800	1.1	16T #30 on T30-2	14	57T #30 on T30-2	T30-2	16T #30	7T/7T #30 bifilar
3.500	470	470	220	330	1000	360	1000	1.4	18T #30 on T30-2	3.9	30T #30 on T30-2	T30-2	18T #30	8T/8T #30 bifilar
7.000	270	270	47	150	470	180	470	0.73	13T #26 on T30-2	1.9	21T #26 on T30-2	T30-2	13T #26	6T/6T #26 bifilar
10.100	270	270	47	100	330	120	330	0.52	11T #26 on T30-2	1.2	17T #26 on T30-2	T30-2	11T #26	5T/5T #26 bifilar
14.000	180	180	47	47	270	100	270	0.36	10T #26 on T30-6	0.92	16T #26 on T30-6	T30-6	10T #26	5T/5T #26 bifilar
18.068	150	150	47	47	180	69	180	0.36	10T #26 on T30-6	0.71	14T #26 on T30-6	T30-6	10T #26	5T/5T #26 bifilar
21.000	150	150	47	47	150	62	150	0.29	9T #26 on T30-6	0.61	13T #26 on T30-6	T30-6	9T #26	4T/4T #26 bifilar
24.890	120	120	47	47	120	47	120	0.24	8T #26 on T30-6	0.52	12T #26 on T30-6	T30-6	8T #26	4T/4T #26 bifilar
28.000	100	100	47	33	120	47	120	0.18	7T #26 on T30-6	0.44	11T #26 on T30-6	T30-6	7T #26	3T/3T #26 bifilar